

sound services PMX-160



* shown with optional loudspeakers

PMX160 - 160w amplifier from IMG Stageline

Powered mixer 160w RMS - /240wMAX into 4Ω

- * Audio mixer and audio amplifier built into a wooden housing with black plastic covering
- * 4 mono input channels, each with gain control, 2-way tone control and effect control
- * 2 stereo input channels, each with gain control, 2-way tone control and effect control
 - * Adjustable digital reverb
 - * Adjustable effect way
- * Tape record and CD/tape play connections
- * 15V phantom power, can be switched centrally
 - * 5-band graphic equalizer
 - * LED level display

Frequency range - 20-20,000Hz

Input sensitivity - 1.5mV (mic), 50mV (line), 240mV (tape), 1V (effect return)

Outputs - 540mV (tape rec.), 1V (effect send)

S/N ratio - 77dB

THD - 0.1%

Equalizer - Bass ±15dB/60Hz, Treble ±15dB/15kHz

Graphic equalizer ±12dB, 60, 250, 800, 2000, & 8000 Hz

Power supply - 230v AC - 50Hz - 370va

Admiss. ambient temp. - 0-40 °C

Dimensions - 440x200x305mm

Weight - 10.6kg