



Sound Services

SS1000 earband and SS2000 headband (headmic) subminiature electret microphones

Headband and earband electret condenser microphones for use with radiomic transmitters available with:

- 3.5mm jack connector – order suffix **J**
- 3 pin mini XLR for IMG Stageline, Gemini 64ch etc. – order suffix **X3**
- locking 3.5mm jack - female thread for newer Sennheiser & Trantec, IMG Stageline etc. – order suffix **LJ**
- 4 pin mini XLR for Shure – order suffix **X4**
- 3 pin mini XLR for AKG – order suffix **AKG**
- Lemo for older Trantec – order suffix **Lemo**
- 4 pin HRS for Audio-Tecnica – order suffix **HRS**

SS1000 earband / earhook microphone

- Directivity: Omni Directional
- Frequency Response: 20Hz to 20kHz
- Lead Length: 1m
- Output Impedance: 1.1kohm
- Sensitivity: -65dB
- Colour: Beige
- Supply Bias Voltage: 1 to 10V dc (2 wire configuration)
- Weight: 3.4g

SS2000 headmic / headworn microphone

- Directivity: Omni Directional
- Frequency Response: 20Hz to 20kHz
- Lead Length: 1m
- Output Impedance: 1.1kohm
- Sensitivity: -65dB
- Colour: Beige
- Supply Bias Voltage: 1 to 10V dc (2 wire configuration)
- Weight: 12.2g