



MMX-602

Order No. 20.1740



Microphone line mixer, 6 channels.

- 6 stereo line inputs, 6 balanced mono microphone inputs, switchable
- Adjustable automatic talkover (-12dB), switchable for channel 1 or channels 1+2
- Balance controls for the stereo input channels
- 3-way equalizer
- Optional 12V phantom power
- LED VU meter, peak LED
- Master output and record output
- Output can be switched stereo/mono
- Adjustable headphone output
- 482mm (19") rack installation, 1RS



Model	MMX-602
Line input, stereo	100mV/10kΩ
Microphone input	1mV/15, 6kΩ
Master output, stereo	1V/500Ω
Record output, stereo	310mV/500Ω
Headphones, stereo	> 8Ω
Frequency range	20-2,000Hz
THD	0.1%
SN ratio	62dB, unweighted
Equalizer, bass	±12dB/50Hz
Equalizer, midrange	±12dB/1k Hz
Equalizer, treble	±12dB/10k Hz
Power supply	230V~/50Hz/12VA
Admiss. ambient temp.	0-40 °C
Dimensions	482x47x208mm, 1RS
Weight	2.8kg
Line input, stereo	6 x phono LR
Microphone input	6 x XLR, bal.
Master output, stereo	1 x phono LR, 1 x XLR LR, bal.
Record output, stereo	1 x phono LR
Headphones	1 x 6.3mm jack

