

Stage Line MPX80 stereo 8 input mixer



8-channel stereo audio mixer especially suitable for PA and DJ applications.

- 2 mono microphone channels with switchable gain control (+20dB) and talkover
- 6 stereo input channels, switchable phono/line (channels 3+4) or line/line (channels 5-8)
- Gain control, channel fader, and 3-way equalizer with centre click for each input channel
- 1 stereo master output, switchable mono/stereo
- 1 stereo record output for connecting a recorder
- 3-way equalizer with centre click for the master output and record output
- Pre-fader listening to all stereo input channels and the master output via adjustable stereo headphone output
- Stereo LED level display for master and PFL

Inputs

Mic, mono	0.3-3mV/3-30mV
Phono, stereo	1.5-15mV
Line, stereo	50-500mV (ch. 3/4) 100mV-1V (ch. 5-8)

Outputs

Master, stereo	7.5V/600Ω
Record, stereo	7.5V/600Ω
Headphones, stereo	≥8Ω

Frequency range 20-20,000Hz

THD 0.1%

S/N ratio 66dB, unweighted

Equalizer

Bass	±10dB/80Hz
Midrange	±10dB/1kHz
Treble	±10dB/10kHz
Talkover	-14dB
Power supply	230V~/50Hz/15VA
Dimensions	482x90x190mm, 2RS
Weight	3.8kg