



PMX100 - 100w powered mixer from IMG Stageline

- Mixer and amplifier built into a wooden sleeve with black vinyl covering
- 4 mono input channels each suitable for microphone, radiomic or line inputs
- Treble tone control on each input channel
- 3-way equalizer for master output
- Connection for a foot switch for switching the reverb effect on and off
- Adjustable spring reverb for all inputs
- +15V phantom power

RMS output power	100w RMS into 4Ω
Frequency response	20-20,000Hz
Input impedance	3.5kΩ 100kΩ
Input sensitivity	1.5mV (mic) 20mV (line)
S/N ratio	51dB
THD	≤ 0.2%
Bass	±15dB/30Hz
Mid range	±15dB/600Hz
Treble	±15dB/12kHz
Power supply	230V~/50Hz/160VA
Dimensions	465x158x290mm
Weight	9.3kg