



IMG Stageline / Monacor VMX440 mixer

Mixing made easy! An easy-to-use operating concept and clearly arranged features. Two stereo line sources and two mono microphone sources can be mixed together without any problems. Each input channel features a tone control. The master output level can be preadjusted via recessed trimming potentiometers in order to protect against overload. An optional remote switch can mute the stereo master outputs.

- 2 stereo line inputs
- 2 balanced microphone inputs
- Parallel stereo line input at the front panel
- 3-way equalizer for each microphone input
- Common 2-way tone control for the two line inputs
- Mute via optional momentary push-button or switch
- 2 adjustable stereo master outputs
- Master output level can be preadjusted via trimming potentiometers
- Adjustable headphone output
- Stereo record output
- 482mm (19") rack installation, 1RS, with supplied mounting brackets

Line input, stereo	100mV/10kΩ
Microphone input	1mV/600Ω
Master output, stereo	1-3V/100Ω
Record output, stereo	1V/100Ω
Headphones, stereo	≥32Ω, 2 x 15mW
Frequency range	20-20,000Hz
THD	0.05%
S/N ratio	>60dB
Equalizer, bass	±12dB/30Hz
Equalizer, midrange	±12dB/1kHz (voice only)
Equalizer, treble	±12dB/12kHz
Power supply	230V~/50Hz/10VA
Admiss. ambient temp.	0-40 °C
Dimensions	482x45x274mm, 1RS
Weight	2.9kg
Line input, stereo	3 x RCA L/R
Microphone input	2 x 6.3mm jack, bal.
Master output, stereo	2 x RCA L/R
Record output, stereo	1 x RCA L/R
Headphones	1 x 6.3mm jack
Mute	screw plug connection